

 ICOM

HF/50MHz ALL MODE TRANSCEIVER

IC-703

Rugged
MIL-STD 810



Icom Inc.

IC-706 LEGACY, NOW IN A QRP VERSION

Don't sacrifice big rig features just because you want to operate QRP!

Whether hiking in the mountains or taking a leisurely stroll through the park, the IC-703 is the "Real Deal" HF QRP rig! Built-in is an automatic antenna tuner and DSP*, plus there's a newly designed PA circuit to provide a clean 5W signal with only 9.6V DC. The IC-703 also supports true QRP operation with enhancements of features and components to be very efficient to prolong operation of the battery pack. The optional BP-228 battery pack allows up to 7 hours of operating enjoyment. *Optional UT-106 required depending on version.



HF how it should be: Compact and Portable!

Designed by hams, for hams! Take your hobby with you into the great outdoors with the LC-156, Icom's Multi-bag '703 carrier. The LC-156 offers plenty of room to store and protect the gear you'll want to bring along for hours of fun operating the bands. It's the perfect way to combine a ham's love for both the hobby and the great outdoors!

The recommended way to pack your IC-703

The rain cover is included in the multi-bag. Use the loops to secure your portable antenna for safe travel. Great for portable use, the handy controller case can be easily removed from the multi-bag and attached to your belt. Pouches for stowing controller and hand mic when not in use. Microphone hanger. Cable exit for separation and coaxial cables, when connected to the IC-703 in the bag. Pouch for stowing coaxial cables. Controller pouch secured on multi-bag. DC power cables. Storage area for the optional BP-228 battery pack. Storage area for IC-703. Pouch for stowing the microphone. Repositionable protection pad, allowing you to customize the size of the storage space. Carry your log book here. Storage area for the optional separate cable, OPC-581/OPC-587. Exterior loops securely hold an antenna to the backpack. During portable operation, make sure not to harm other people or environments.

Icom's DSP technology allows you to pick-out the weak signals!

DSP capabilities give you tools to reduce interfering signals, or just to dig weak signals out of the dirt. The noise reduction separates desired signals from noise and reduces the noise components for a clearer received signal, while the auto notch tracks and eliminates interference from a solid tone signal.




* Optional UT-106 required depending on version.

160-6m full coverage internal automatic antenna tuner, and low current PA

The newly designed PA unit and antenna tuner, specifically designed for the IC-703, extends operating time by reducing the voltage and current consumption. The antenna tuner utilizes low current latching relays to cover 160-6m. While on a 9.6V DC source or less than 11V DC, many functions of the IC-703 are controlled by the microprocessor to extend the battery life.

While in low current mode, the IC-703 automatically switches to 5W output power (2W AM). While on 13.8V DC, the output switches to 10W (4W AM).




Antenna tuner

HF/50MHz ALL MODE TRANSCEIVER IC-703

Auto power scale meter

There's no need to calculate the output power, as the IC-703 automatically scales the power meter according to the output power of the rig. The full scale reading of the meter will indicate the power output setting of the rig. For example, if you are running at 5W mode, the full scale reading will be 5W. (Available power settings are 10/5/2.5/1/0.5W)



Large characters offer an easy to read 5W maximum output.

Low current mode

By using power efficient components for the PA, antenna tuner and the PLL circuits, the IC-703 is designed for maximum efficiency at 9.6V DC. When using the optional BP-228 battery pack, the IC-703 automatically switches into low current mode, thus allowing operation time of up to 7 hours*. While operating on high power, or 13.8V DC, the IC-703 can safely operate at a full 10W even if the power source drops to 11V DC.



To extend battery life, the back lighting for the display and buttons automatically turns off when unused.

* Tx:Rx:Stand-by =0.5:0.5:9 in SSB mode.

Stay on frequency, indoors or out

Whether safe indoors or exposed to the cold temperatures outdoors, the IC-703 will be right on frequency with the standard ± 0.5 ppm TCXO.



Close up of the TCXO circuit

High sensitivity

The IC-703's receiver performance is in the same class as that of high end base stations: 0.16 μ V at 10dB S/N for 1.8 to 30MHz bands and 0.13 μ V for 50MHz at 10dB S/N (in SSB and CW modes).

Remote control head allows for easy operation while outdoors

Operate while hiking without fumbling for the controls. Use with the optional OPC-581 (3.5m; 11ft) or OPC-587 (5m; 16ft) separation cables to remote the control head where its easy to see and use, allowing the compact body, measuring only 167(W) \times 58(H) \times 200(D) mm* and weighing 2.0kg, to be carried out of the way.

*6 $\frac{9}{16}$ \times 2 $\frac{9}{32}$ \times 7 $\frac{7}{8}$ in; 4.4lb



Built-in memory CW keyer

The IC-703 has a built-in CW Memory Keyer with three memory locations and up to 50 characters per memory location. Other keyer features include a variable CW pitch control (300–900Hz); operation with a bug; iambic paddles; or straight key. All these functions are available even when in low current mode.



The memory keyer

Clean FSK, RTTY

Utilizing the TRUE RTTY mode, FSK, the IC-703 generates the tones internally for the cleanest possible signal on the band. Also, whether operating FSK or AFSK data, you can tweak the IC-703 to be the perfect portable RTTY machine by adding the optional FL-52A filter.

455kHz IF filter selections

The 455kHz IF allows you to upgrade the standard 455kHz filter, FL-65, to improve your selectivity by installing an optional filter into the filter slot.

Built-in SWR analyzer

Check out your antenna's SWR with the internal SWR analyzer. The resolution of the IC-703's SWR graph bandwidth is adjustable from 10/50/100/500kHz.



Graphing the SWR

Band scope

Catch band activity at a glance with the band scope. With the operating frequency in the center of the display, each step either to the left or right of center is selectable from 0.5/1/2/5/10/20/100 kHz steps.



The band scope

Other outstanding features

- 30kHz–60MHz general coverage receive (depending on version)
- Built-in pre-amplifier
- IF shift function with graphical indication
- AGC time constant setting
- 20dB (approx.) RF attenuator
- AF Speech compressor
- CTCSS tone encoder/decoder for repeater access
- VOX function
- All mode power control
- Split operation with receive frequency lock
- CI-V system capability
- 9600bps data terminal on rear panel
- Amber LCD backlight
- Bandstacking register
- Combined SQL and RF gain control knob
- Total 105 memory channels
- Optional voice synthesizer, UT-102
- Variable SSB carrier-point
- Fanless noise free operation
- Vertically stands upright on its base
- Band edge beep and more...

Rear View



SPECIFICATIONS

GENERAL

- Frequency coverage* :
 - Receive 0.030–60.000MHz
 - Transmit 1.800– 1.999MHz 3.500– 3.999MHz
 - 5.000– 5.499MHz 7.000– 7.300MHz
 - 10.100– 10.150MHz 14.000– 14.350MHz
 - 18.068– 18.168MHz 21.000– 21.450MHz
 - 24.890– 24.990MHz 28.000– 29.700MHz
 - 50.000– 54.000MHz
- * Frequency range varies and some frequency ranges are not guaranteed depending on version. 5MHz and 50MHz bands available depending on version.
- Mode : USB, LSB, CW, RTTY, AM, FM
- No. of channels : 105 (99 regular, 6 scan edges)
- Antenna impedance : 50Ω (SO-239)
- Power supply requirement : 9–15.8V DC
- Operating temp. range : -10°C to +60°C; +14°F to +140°F
- Frequency stability : Less than ±0.5ppm (+0°C to +50°C)
Less than ±2.5ppm (-10°C to +60°C)
- Output power and current drain :

	at 13.8V	at 9.6V
Output Power	SSB/CW/RTTY/FM 0.1–10W	0.1–5W
AM	0.1–4W	0.1–2W
Transmit	High (typical) 3.0A (at 10W)	2.0A (at 5W)
Receive	Max. audio 1.2A	450mA typ.
Stand-by	–	300mA typ.

- Dimensions (W×H×D) : 167 × 58 × 200 mm; (projections not included) 6⁵/₁₆ × 2³/₃₂ × 7⁷/₈ in
- Weight : 2.0kg; 4.4lb
- CI-V connector : 2-conductor 3.5 (d) mm (1/8")

TRANSMITTER

- Modulation system : SSB Balanced modulation
AM Low level modulation
FM Variable reactance modulation
- Spurious emissions : Less than -50dB (Below 30MHz)
Less than -60dB (Above 50MHz)
- Carrier suppression : More than 40dB
- Unwanted sideband suppression : More than 50dB
- Microphone connector : 8-pin modular jack (600Ω)
- CW KEY connector : 3-conductor 6.35 (d) mm (1/4")

RECEIVER

- Receive system : Double conversion superheterodyne
- Intermediate frequency : 1st/2nd 64.455/0.455MHz

	SSB/CW/RTTY (at 10dB S/N)	AM (at 10dB S/N)	FM (12dB SINAD)
0.5– 1.8MHz	–	13μV	–
1.8– 28MHz	0.16μV*	2μV*	–
28– 29.7MHz	–	–	0.5μV*
50MHz band	0.13μV*	1μV*	0.25μV*

- * Pre-amp on
- Sensitivity (typical) : SSB 5.6μV typ.
FM 0.32μV typ.
- Squelch sensitivity (threshold; pre-amp on) : FM 0.32μV typ.
- Selectivity : SSB, CW (2.4kHz) More than 2.4kHz/–6dB

- AM/FM-N (6kHz) : Less than 4.0kHz/–60dB
More than 9.0kHz/–6dB
Less than 20kHz/–50dB
- FM (15kHz) : More than 15kHz/–6dB
Less than 30kHz/–50dB
- Spurious and image rejection ratio:
 - HF bands : More than 70dB
 - 50MHz : More than 65dB (except IF point)
- Audio output power (8Ω load, 10% distortion) : More than 1.0W (at 13.8V DC)
More than 0.5W (at 9.6V DC)
- RIT variable range : ±9.99kHz
- PHONES connector : 3-conductor 3.5 (d) mm (1/8")
- EXT SP connector : 2-conductor 3.5 (d) mm (1/8")/8Ω

Applicable U.S. Military Specifications


Standard	MIL 810 C		MIL 810 D		MIL 810 E		MIL 810 F	
	Method	Proc.	Method	Proc.	Method	Proc.	Method	Proc.
Low Pressure	500.1	I	500.2	I, II	500.3	I, II	500.4	I, II
High Temp.	501.1	I	501.2	I, II	501.3	I, II	501.4	I, II
Low Temp.	502.1	I	502.2	I, II	502.3	I, II	502.4	I, II
Temp. Shock	503.1	I	503.2	I	503.3	I	503.4	I
Solar Radiation	505.1	I	505.2	I	505.3	I	505.4	I
Rain	506.1	I	506.2	I	506.3	I	506.4	I
Humidity	507.1	I, II	507.2	II, III	507.3	II, III	507.4	–
Salt Fog	509.1	I	509.2	I	509.3	I	509.4	–
Dust	510.1	I	510.2	I	510.3	I	510.4	I
Vibration	514.2	VIII, X	514.3	I	514.4	I	514.5	I
Shock	516.2	I, II, V	516.3	I, IV	516.4	I, IV	516.5	I, IV

Supplied accessories:

- Hand microphone
- DC power cable
- Spare fuses
- Key plugs
- ACC cable

All stated specifications are subject to change without notice or obligation.

OPTIONS




• **BP-228 BATTERY PACK**
Ni-Cd 9.6V/2800mAh. Provides 7 hours of operating time. (approx.)




• **BC-155A/D BATTERY CHARGER**
Charges the BP-228 in 8 hours. (approx.)



• **LC-156 MULTI-BAG**
Carrying case for field operation. Controller case and rain cover are attached.



• **MB-62 MOBILE MOUNTING BRACKET**
For mounting the IC-703 main unit or the AT-180.



• **MB-63 MOBILE MOUNTING BRACKET**
For mounting the detached front panel.



• **MB-65 MOUNTING BASE**
For mounting the detached front panel in a vehicle. Optional MB-63 is required.



• **MB-72 CARRYING HANDLE**
Convenient for carrying in the field, etc.



• **OPC-581/OPC-587 SEPARATION CABLES**
OPC-581: 3.5m (11ft)
OPC-587: 5m (16ft)



• **UT-102 VOICE SYNTHESIZER UNIT**
Provides audible confirmation of frequency and mode in English.



• **UT-106 DSP UNIT**
Provides DSP functions such as noise reduction and auto notch. Already built-in to some versions.



455kHz FILTERS
Have a good shape factor and provide you with better reception.

Select one of these filters.

- **FL-52A** 500Hz/–6dB (CW/RTTY narrow)
- **FL-53A** 250Hz/–6dB (CW narrow)
- **FL-222** 1.8kHz/–6dB (SSB narrow)
- **FL-257** 3.3kHz/–6dB (SSB wide)



• **AH-703 HF/50MHz 5-BAND ANTENNA**
Covers 7, 14, 21, 28, 50MHz bands. Max. length : 1.4m; 4.5ft.

EXTERNAL ANTENNA TUNERS & ELEMENT

- **AH-2b ANTENNA ELEMENT**
2.5m (8ft) antenna element for mobile operation with the AH-4. All bands between 7–54MHz can be matched.
- **AH-4 HF+50MHz AUTOMATIC ANTENNA TUNER**
For use with the long wire antenna matches 3.5–54MHz.
- **AT-180 HF+50MHz AUTOMATIC ANTENNA TUNER**

OTHERS

- **CT-17 CI-V LEVEL CONVERTER**
- **HM-103 HAND MICROPHONE** (same as supplied)
- **OPC-589 MODULAR 8-PIN CABLE ADAPTER**
- **OPC-598 ACC 13 PIN LONG CABLE FOR AT-180 (7m; 22ft)**
- **OPC-599 ACC 13 PIN CABLE ADAPTER**
- **OPC-1248 POWER SUPPLY ADAPTER**
Connects 3-pin DC cable to 6-pin connector.
- **PS-125 DC POWER SUPPLY**
Compact power supply. Output: 13.8V DC (25A max.). Use with OPC-1248.
* The IC-703 may receive switching noise from the PS-125, when used with a compact mobile type antenna.
- **SM-20 DESKTOP MICROPHONE** (Optional OPC-589 is required.)
- **SP-10 EXTERNAL SPEAKER**

Icom Inc. 1-1-32, Kamiminami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.
2380 116th Avenue NE,
Bellevue, WA 98004, U.S.A.
Phone: +1 (425) 454-8155
Fax: +1 (425) 454-1509
E-mail: sales@icomamerica.com
URL: <http://www.icomamerica.com>

Icom New Zealand
146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone: +64 (09) 274 4062
Fax: +64 (09) 274 4708
E-mail: inquiries@icom.co.nz
URL: <http://www.icom.co.nz>

Icom (UK) Ltd.
Unit 9, Sea St., Herne Bay,
Kent, CT6 8LD, U.K.
Phone: +44 (0)1227 741741
Fax: +44 (0)1227 741742
E-mail: info@icomuk.co.uk
URL: <http://www.icomuk.co.uk>

Asia Icom Inc.
6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone: +886 (02) 2559 1899
Fax: +886 (02) 2559 1874
E-mail: sales@asia-icom.com
URL: <http://www.asia-icom.com>

Your local distributor/dealer:

Icom Canada
Greenwood Centre #150-6165 Highway 17,
Delta, B.C., V4K 5B8, Canada
Phone: +1 (604) 952-4266
Fax: +1 (604) 952-0090
E-mail: info@icomcanada.com
URL: <http://www.icomcanada.com>

Icom (Europe) GmbH
Communication Equipment
Himmelgeister Str. 100,
D-40225 Düsseldorf, Germany
Phone: +49 (0)211 346047
Fax: +49 (0)211 333639
E-mail: info@icom-europe.com
URL: <http://www.icomeurope.com>

Icom France S.a
Zac de la Plaine, 1,
Rue Brindejonc des Moulains BP 5804,
31505 Toulouse Cedex, France
Phone: +33 (5) 61 36 03 03
Fax: +33 (5) 61 36 03 00
E-mail: icom@icom-france.com
URL: <http://www.icom-france.com>

Beijing Icom Ltd.
10C07, Long Silver Mansion, No.88, Yong Ding
Road, Haidian District, Beijing, 100039, China
Phone: +86 (010) 5889 5391/5392/5393
Fax: +86 (010) 5889 5395
E-mail: bjicom@bjicom.com
URL: <http://www.bjicom.com>

Icom (Australia) Pty. Ltd.
A.B.N. 88 006 092 575
Unit 1 / 103 Garden Road,
Clayton VIC 3168 Australia
Phone: +61 (03) 9549 7500
Fax: +61 (03) 9549 7505
E-mail: sales@icom.net.au
URL: <http://www.icom.net.au>

Icom Spain S.L.
Ctra. Rubi, No. 88 "Edificio Can Castanyer"
08190, Sant Cugat del Valles, Barcelona, Spain
Phone: +34 (93) 590 26 70
Fax: +34 (93) 589 04 46
E-mail: icom@icomspain.com
URL: <http://www.icomspain.com>

Icom Polska
Sopot, 3 maja 54, Poland
Phone: +48 (58) 550 7135
Fax: +48 (58) 551 0484
E-mail: icompolksa@icompolksa.com.pl
URL: <http://www.icompolksa.com.pl>

Icom Inc. (Japan), is an ISO 9001 and ISO 14001 certification acquired company.